



Features & Benefits

- Magnetic reed switch
- Button
- Temperature sensor

Technical Overview

Open/Close LoRaWAN® sensor is a device detecting the event of opening or closing windows, doors, cabinets and more. It features a long battery life, LED, temperature sensor and a button that triggers an uplink. The device sends an uplink for every event of opening/closing and keeps an internal counter of the total number of events.

Technical Specification

Radio output type	LoRaWAN 1.0.3
Frequency Range	EU863–870; Other LoRaWAN regional settings available upon request
Security	End-to-End encryption (AES-CTR)
Batteries	ER14250 or 1/2 AA (included in the device)
Battery Life	5-10 Years (depending on configuration and environment)
Housing colour	White
Housing Dimensions	72 x 20mm & 50 x 10mm
Country of origin	Bulgaria

Related Product Codes

RF-LW-OC	LoRaWAN Open/ close sensor
-----------------	----------------------------